

INSTRUCTION SHEET

CPDB 160, CPDB 250, CPDB 400


(2112101926, 2112101928, 2112101922, 2112101929)



SEP One pole DIN-rail distribution block, 160A / 11,8kA

CPDB 160A

2112100160




SEP One pole DIN-rail distribution block, 250/400A / 24,5kA

CPDB 250

2112100250

CPDB 400

2112100400



						CPDB160 2112100160	CPDB250 2112100250	CPD400 2112100400
→	4 Nm	10mm ² - 70mm ²	10mm ² - 70mm ²	HEX 5	○	1x		
→	19 Nm	35mm ² - 120mm ²	35mm ² - 95mm ²	HEX 6	○		1x	
→	25 Nm	35mm ² - 185mm ²	35mm ² - 150mm ²	HEX 8	○			1x
←	2 Nm	2,5mm ² - 10mm ²	1,5mm ² - 10mm ²	M4	⊕		4x	4x
←	2 Nm	2,5mm ² - 16mm ²	1,5mm ² - 16mm ²	M4	⊖	6x	5x	5x
←	3,5 Nm	6mm ² - 35mm ²	2,5mm ² - 25mm ²	M4	⊖		2x	2x

Note:

Unused openings should be tighten to a torque of 0,5 - 1 Nm

WARNING:

All products shall be installed and used as indicated by SEP Europe in the instruction sheets and training materials. Products must never be used for a purpose other than which they were designed for or in a manner that exceeds the specified ratings. Installations must be carried out in accordance with the applicable national rules for electrical installations.

SEP Europe® is owned by Schotman Elektro BV®. All other trademarks are the property of their respective owners. Schotman Elektro BV reserves the right to change specifications without prior notice.

Registered in Netherlands No. 01108453

2020IS-SEP-CPDB160-250-400